

MP610P

250W 6 Zones Mixer Amplifier



Description

This mixing amplifier has 6 zones selector, and each zone has its individual volume control. Rated at 250W, it has 2 unbalanced microphones inputs and 3 aux inputs. Bass and treble controls and master volume control are provided.

This amplifier can be applied to different cases, such as supermarket, classroom, etc.

Features

- 6 zones speaker output, each zone with individual volume control;
- 2 Mic inputs, Mic 1 with priority and muting function
- 3 AUX line inputs & 1 AUX line output for power extension
- Each AUX & Mic input with individual volume control
- With bass and treble tone control for speaker output
- Built-in chime for speech/ paging notification
- 100V & 4-16Ω optional speaker output for different uses

Specifications

Model	MP610P
Rated output	250W
Speaker output	100V & 4-16 Ω,
Input sensitivity	Mic less than 3.5mV line less than 300mV

Frequency response	80Hz -16kHz (± 3 dB)
Distortion	Less than 0.5% (1kHz, normal working station)
Protection	AC fuse; DC voltage; overload; short-circuit.
Power requirements	AC 220V/50Hz
Power consumption	500W
Rated output	250W
Outer Packing Size (mm)	(L×W×H) 555×455×185
Unit Size (mm)	(L×W×H) 484×355×88
Gross weight	16kg
Net weight	14kg